

Facility Planning Data Sheet

2033A DDC Series 30 - 75 kVA UPS (208in/208out, 600in/600out, 600in/208out)

Power Rating		UPS AC Input							Battery System			AC Output			Mechanical Information				
		Voltage		kVA		Current		Minimum Input	External Overcurrent Protection	Nominal Voltage	Full Load	Maximum Discharge	Voltage	Current Nominal	External Overcurrent Protection	Dimensions W x D x H	Weight	Floor Loading	Heat Rejection
kVA	kW	Vac/ Freq.	Nom.	Max.	Nom.	Max.	AWG or kcmil		VDC	kW	A	Vac	A		Inch	Lbs	Lbs/ Ft ²	kBTU/ Hr	CFM
30	24	208 / 60Hz	27.8	30.9	77	86	2 or larger	110A	360	26.2	90	208	83.3	110A	35.4x29.5x70.9	1,050	145	11.0	1160
30	24	600 / 60Hz	29.5	32.8	28.4	31.5	8 or larger	40A	360	26.2	90	600	28.9	40A	59.5x29.5x70.9	2,250	184	17.7	1880
30	24	600 / 60Hz	29.5	32.8	28.4	31.5	8 or larger	40A	360	26.2	90	208	83.3	110A	51.4x29.5x70.9	1,800	171	17.7	1880
50	40	208 / 60Hz	45.9	51.5	127	143	2/0 or larger	175A	360	43.7	151	208	138.9	175A	43.3x29.5x70.9	1,470	166	16.9	1790
50	40	600 / 60Hz	29.5	32.8	28.4	31.5	8 or larger	40A	360	43.7	151	600	48.1	60A	67.3x29.5x70.9	2,820	204	22.9	2430
50	40	600 / 60Hz	29.5	32.8	28.4	31.5	8 or larger	40A	360	43.7	151	208	138.9	175A	67.3x29.5x70.9	2,400	174	22.9	2430
75	60	208 / 60Hz	68.7	77.3	191	215	300 or larger	300A	360	65.6	226	208	208.2	300A	43.3x29.5x70.9	1,700	191	25.0	2650
75	60	600 / 60Hz	29.5	32.8	28.4	31.5	8 or larger	40A	360	65.6	226	600	72.2	90A	67.3x29.5x70.9	3,160	229	34.1	3620
75	60	600 / 60Hz	29.5	32.8	28.4	31.5	8 or larger	40A	360	65.6	226	208	208.2	300A	67.3x29.5x70.9	2,660	193	34.1	3620
Notes:				1	2	3,4,10,13,A,B,C		4,7,9	5	6,10		1		4,7,8,11	11,12				

Notes:

- Nominal (Nom.) current based on rated load.
- Maximum (Max.) current based on converter overload rating.
- Input and output cables typically run in separate conduits.
- If initial load is less than UPS' rated output, it is recommended that AC input, battery, and AC output wiring and overcurrent protection be sized to UPS' full load rating to accommodate possible future expansion.
- Nominal battery voltage assumed to be 2.0 volts/cell (lead technology).
- DC cables should be sized for not more than a 2.0% line drop at maximum discharge current.
- Suggested AC output overcurrent protection based on continuous full load current per CEC Rules 30-714 and 34-018. 80% rated breakers assumed.
- Grounding conductors to be sized per CEC Table 16 and applicable rules. Neutral conductors to be sized per CEC Rule 4-022.
 - AC Input: 3 ϕ , 3 wire, ground.
**For single input feed, neutral conductor required for bypass.
 For single input feed, jumper bypass and converter phase conductors.**
 - Bypass Input: 3 ϕ , 4 wire + ground.
 - AC Output: 3 ϕ , 4 wire + ground.
 - DC Input: 2 wire (Positive and Negative) + ground.
- Input neutral conductor not required since main feed supplied from a delta-wye input isolation transformer. Neutral derived on wye side.
- All wiring to be in accordance with all applicable national and/or local electrical codes.
- Minimum access clearance per UPS drawings or Owner's Manual.
- Cable entry from top or bottom. Punch plates accordingly. (*Side access possible. Consult MEPPI for specifics.*)
- Control wiring and power wiring to be run in separate conduits.

Additional Notes:

- For site configurations including emergency generators, engine generator to be sized and equipped for UPS applications. Generator equipped with governor for frequency regulation and regulator for voltage stability recommended. Note: UPS' reflected current distortion is 3% max at full load and 6% max at 50% load.
 - For site configurations equipped with an external Maintenance Bypass Switch circuit, UPS must be on internal Static Bypass before transferring to external Maintenance Bypass. Consult Factory for further information.
 - For site configurations including automatic transfer switches, transfer switch to be equipped with "neutral delay position" option to minimize phase shift during operation. Transfer switch equipped with auxiliary contact for control of UPS input current when on generator recommended. Consult transfer switch manufacturer for required transfer switch options and sizing.
- A. Not more than 3 conductors in raceway assumed; ambient temperature of 30 °C (86 °F) assumed.
- B. Temperature rating of conductors: 75 °C (167 °F). Reference Table 2 of CEC, 75 °C column, using copper conductors. 75 °C (167 °F) cable terminal connectors assumed.
- C. Reference: CEC handbook 1994. Consult local codes for possible variations.
- D. RATINGS OF CABLES AND OVERCURRENT DEVICES SUPPLIED FOR INFORMATION ONLY. USER TO CONSULT WITH ITS ENGINEERING SERVICES BEFORE ADOPTING.**



Mitsubishi Electric Power Products, Inc.
 UPS Division
 Phone: (724) 772-2555 Fax: (724) 778-3146

EMERGENCY SERVICE
1-877-251-0111
CALGARY - EDMONTON - VANCOUVER - SASKATOON